

MakeUp Aria - MA.ABS.4C.0.1 rev. 1.1_27/07/2023

General description

Wireless controllable, keypad for operation control with feedback led. The buttons can control a scene or an animation of the user's choice or simply one luminaire, one luminaire group or all lamps together if so desired if used with PLH Aria dimmers or any lighting fixture powered by Casambi or a PLH Aria Jellyfish output interface.

To be configured with Casambi app available for iOs (iPhone 4S or later, iPad 3 or later, iPod Touch 5th gen or later) and Android devices (Android 4.4 KitKat or later devices produced after 2013 with full wireless support).

Technical specifications

Programmable push buttons	4
Type of inputs	Tact switch
Operating life	500.000 cycles
Feedback	Led blue on board
Battery type	3V CR2032 lithium coin cell
Lyfetime	10.000 click
Maximum output radio transceiver power:	-9,15 dBm
Range (depending on the surrondings)	up to 10 m
Contains FCC ID:	2ALA3-CBM002A
Contains IC	22496-CBM002A
Dimensions:	90 x 90 x 10 mm (3,54 x 3,54 x 0,39 inches)
Case	Polycarbonate body and buttons in aluminium
Weight:	100 g
Degree of protection:	IP20 (indoor use only)
Ambient temperature, ta:	- 20 + 45 °C
Max. case temperature, tc:	+ 65 °C
Max. relative humidity:	080%, non-cond.
Mark and regulations	CE

Casambi Profile

3663 4 push buttons

How to use it

Check the instructions below for the configuration.

PLH MakeUp Aria is provided with 4 programmable buttons:



How to change the battery

Pull out gentle the front plate from the wall . Release the old battery sliding it, and change with the new one CR2032. Respect the + symbol on the top.

Click the push button and check the functionality and the blue led on. Reinsert the front plate.





Ν



MakeUp Aria

cod. MA.ABS.4C.0.1

Warranty

We reserve the right to make technical and formal changes to the product in the interest of technical progress. Our products are under guarantee within the scope of the statutory provisions. If you have a warranty claim, please contact PLH by e@mail (support@plhitalia.com) or the Local Reseller.



This product should not be disposed of with household waste.

Please recycle the products where facilities

for electronic waste exist. Check with your local authorities for recycling advice.



MakeUp Aria

cod. MA.ABS.4C.0.1

1. Download the app

Download the free Casambi App directly from the AppStore or the Google Play



For all the functionality of the Casambi App download the Short User Guide from the Casambi website

https://casambi.com/static/datasheets/Shortuser-guide.pdf

2. Open the App

Before you open the app be carefull about this points:

- the wireless connection need to be ON on your smartphone or tablet
- have done all the updates of the operating system;
- have installed and configured a Casambi device or a PLH Dimmer or PLH Jellyfish
- have created a 'Network'



3. Add the device

To add the MakeUp Aria on your network you need to have installed a Casambi enabled lighting fixture, a PLH Dimmer or a PLH Jellyfish. Refer to the specific manual for the installation of those devices.

After you open the Casambi App on your Smartphone, **take pressed** the main button of the MakeUp Aria and a window 'Found a new device' will appear.



Then click on **Add individually to...**, change the Name of your MakeUp Aria, and add to your new network.

Release the button only at the end of the process.



Take in mind that by default the profile is provided with the MakeUp 4P profile.

4. Assign input functionality

To assign and change the preferences of the MakeUp Aria go on **More / Switches** and select your MakeUp Aria

From the beginning all the input will be 'Not in use'.

Tap to select to change the functionality. You can control any Casambi devices or scenarios.



TREBETS		
Push1	Tap to select	>
Push2	Tap to select	>
Push3	Tap to select	>
Push4	Tap to select	>

Use toggle Tapping the button will switch the configured target between OFF and ON (100% or last dim level) INFORMATION Battery Name Makeup

Icon	lap to set 💚
Vendor	PLH
Model	MakeUp 4 PB
Details	>
S Replace device	
Replace this device with a compatible unpaired device so that all settings remain	

unchanged.





Refer to the Casambi App Manual for any further study.

5. Update the firmware

Time to time the firmware update window will appear for some maintanance stuff. Then perform the update clicking on **Start update.**

Don't forget to take pressed the main push button till the update is not ended.

7. Troubleshooting

- The MakeUp Aria is a battery device. If not function check the blue light turn on when you click the main push button. If not, change the battery following the instructions.
- The MakeUp Aria use the wireless signal, for communicate between the devices.
 Refer to the Casambi website to discuss all aspects related to this technology.
- You can control devices in a range up to 10m but it strongly depends by the surrondings. If the 'receiver' device like a Casambi Dimmer, is inside of a metal box this range can reduce significatevely.





www.plhitalia.com



info@plhitalia.com



Devices with soul.